

# ASSEMBLY INSTRUCTIONS



Your new MaCo 103HV MaxiBeam is a new innovation in base station beam design which enables the vertical and horizontal to be assembled for either 10 or 11 meters.

For example, using the charts supplied, you can assembled the horizontal for 11 meters and the vertical for 10 meters or reverse this or assemble both the same. It does not matter. The vertical and the horizontal do not affect each other.

The only difference between the HV Beams and the instructions included is that the HV Beam has both sets of elements on the same boom.


**Please add the following instructions to those supplied:**

Mount the first reflector with the U-Bolt facing the rear. Mount its mate with the U-Bolt facing the front of the beam. This is so the vertical and horizontal elements will be close together.

Do the same with all elements and measure the spacing only once per set of elements.

That's it. Have at it!

If you have any questions or need assistance please call. We're here to help!



**[www.macoantennas.net](http://www.macoantennas.net)**

**(815) 244-3500**

MACo Antennas, A Division of Charles Electronics, LLC  
302 S. East Street, Mt. Carroll, IL 61053

# MACO M103HV

## PACKING LIST

<u>PART</u>	<u>QTY</u>	<u>O.D.</u>	<u>SIZE</u>	<u>LENGTH</u>	<u>DESCRIPTION</u>	<u>CHECKLIST</u>
T59P	1	1-1/2"	.050	72"	ALUM TUBING SWAGED 1 END 6"	___
T28	1	1-1/2"	.050	72"	ALUM TUBING	___
T11P	6	5/8"	.050	72"	ALUM TBNG SLTD BOTH ENDS	___
T04	4	1/2"	.050	80 1/2"	ALUM TUBING	___
T01	8	1/2"	.050	72"	ALUM TUBING	___
P01P	1		1/4" x 5"	5"	PLATE 1-1/2" BOOM TO 1-1/2" MAST	___
G01P	2				GAMMA MATCH	___
Z08P	4				GAMMA STRAPS F/COAX CONNECTS	___
S42	2				FEMALE COAX CONN W/MOUNTING	___

### HARDWARE BAG #1

U02	10		1-1/2"		PLATED U-BOLTS	___
S02	10		1-1/2"		PLATED SADDLES	___
N03	21		5/16"		HEX NUTS	___

### HARDWARE BAG #2

BE1P	6	1-1/2"			BOOM TO ELEMENT MOUNT	___
W58P	12	5/8"			EXTRUDED ALUM CLAMPS	___
S21	22		10-24	1/2"	MACHINE SCREWS	___
PL2	12		.437		PLASTIC CAP - BLACK	___
N11	22		10-24		SQUARE NUTS	___
Z02P	4		1/2"		GAMMA STRAPS	___
N12	8		#10		LOCKWASHER	___
PL4	1		1-1/2"		PLASTIC CAP - BLACK	___
PL4R	1		1-1/2"		PLASTIC CAP - RED	___
	1				INSTRUCTION SHEET	___
	1				WARRANTY SHEET/SAFETY SHEET	___
	1				TIP SHEET	___

WHEN ORDERING PARTS, ALWAYS GIVE PART NUMBER AND DESCRIPTION.

Please note: In an effort to keep the price on Maco Antennas down, we have decided not to clean up all the burrs and rough edges on the parts. We recommend that you deburr and clean up each part with files, sandpaper, etc. so that they go together easily. We are aware this needs to be done but have elected not to do it to save you the money we would have to add to the price of the kit for this service.

**DANGER**

**High Voltage  
Overhead**

**Caution:**

**TAKE CARE TO AVOID ANY CONTACT WITH  
OVERHEAD POWERLINES WHEN RAISING,  
INSTALLING, OR REPAIRING YOUR  
ANTENNA, TOWER, OR ROTOR.**

**DEATH WILL OCCUR!**

Installing and rigging towers, masts and antennas require specialized skills and experience. Information supplied by MACo assumes that all products will be installed by personnel having these skills and have installed similar products before. No one should attempt to install towers or masts without these knowledgeable skills.

MACo assumes no liability if faulty or dangerous installation practices are used. There are available, trained and experienced personnel to assist in installation, maintenance, or disassembly. Contact your local installer if consultation or assistance is required.

All tower and antenna installations should be thoroughly inspected at least twice a year by qualified, experienced, and trained personnel to insure proper performance and safety standards.


### Electrical Warning

An additional warning precaution is given to be careful of surrounding high voltage power wires and other electrical hazards during installation of your tower, rotor, or antenna.

Do not erect a tower, rotor, or antenna during an electrical storm, rainstorm, or when lightning is a possibility.



**Danger of  
Death**



MACo Antennas  
302 S. East Street  
Mt. Carroll, IL 61053

[www.macoantennas.net](http://www.macoantennas.net)  
(815) 244-3500

MACo Antennas is a Division of Charles Electronics, LLC